


PathMaker 100



PathMaker 250

Battery bank combiner

Multiple Battery Bank Charging

PathMaker is a battery combiner that automatically connects two or three battery banks for simultaneous charging and isolates them during discharge. A toggle switch allows the user to manually parallel battery banks for emergency starting power. For use with 12 or 24-volt systems, PathMaker has user adjustable settings for connect and disconnect.

Product Features

- ▶ Automatic, high current switch for simultaneous two to three bank charging
- ▶ Connects batteries together when the voltage is sufficiently high and disconnects when voltage drops during discharge
- ▶ No voltage drop in charging voltage
- ▶ Manual connect feature for emergency starts
- ▶ Compatible with all DC charging sources
- ▶ Convenient front panel LED status indicators
- ▶ User-selectable connect and disconnect voltages
- ▶ Optional Remote Control - indicates Off, Auto and Combine
- ▶ One year warranty

Options

- ▶ Four models available
- ▶ Available in two or three battery bank versions with models at 100 and 250 Amps

Xantrex Technology Inc.

Headquarters
8999 Nelson Way
Burnaby, British Columbia
Canada V5A 4B5
800 670 0707 Toll Free
604 420 1591 Fax

541 Roske Drive, Suite A
Elkhart, Indiana
USA 46516
800 446 6180 Toll Free
574 294 5989 Fax

www.xantrex.com

Battery Bank Combiner**Specifications**

Current ratings	100 A: 100 A continuous, 400 A peak
	250 A: 250 A continuous, 2000 A peak
Voltage range	7 – 33 V (24 V assumed if > 18.0 V)
Low voltage disconnect range	12.8 – 13.2 V (X2 for 24 V)
Connect voltage range	13.1 – 13.5 V (X2 for 24 V)
High voltage disconnect range	14 – 16 V (X2 for 24 V)
Idle power consumed	0.40 W @ 12 V, 0.54 – 1.0 W @ 24 V
Connected power	100 A/2 Bank 7.74 W @ 12 V, 10.78 W @ 24 V
	100 A/3 Bank 13.2 W @ 12 V, 17.4 W @ 24 V
	250 A/2 Bank 2.24 W @ 12 V, 3.69 W @ 24 V
	250 A/3 Bank 3.46 W @ 12 V, 5.43 W @ 24 V
Indicator lights	Disabled: Yellow
	Connected: Green
	High Voltage Disconnect: Red
	Wait for Reconnect: Flashing Red
External control	User supplied momentary on/off switch
Operating temperature range	-28.9°C – 48.9°C (100A), -40°C – 85°C (250A)
Remote panel (optional)	Flush mount, splashproof front, 25' cable included
Dimensions (H x W x D)	100 A: 6.3 x 7.4 x 3.6"
	250 A: 7.6 x 7.4 x 3.2"
Warranty	One year
Weight	100 A/2 Bank: 1.3 lbs.
	100 A/3 Bank: 1.7 lbs.
	250 A/2 Bank: 1.9 lbs.
	250 A/3 Bank: 2.9 lbs.
Part numbers	84-2051-02 (100 A with 2 battery banks)
	84-2051-03 (100 A with 3 battery banks)
	84-2094-01 (250 A with 2 battery banks)
	84-2094-03 (250 A with 3 battery banks)
	84-2053-00 (Remote with 25' cable)

Note: Specifications subject to change without notice.